

# MotionCam Outdoor User Manual

Updated May 19, 2021



**MotionCam Outdoor** is a wireless outdoor motion detector with a camera for alarm verification. Detects movement at a distance of 3 to 15 meters. Has anti-masking protection, ignores animals when correctly configured and installed.



The detector only works with [Hub 2](#) and [Hub 2 Plus](#). Connecting to other hubs, ReX range extenders, and ocBridge Plus and uartBridge integration modules is not supported!

MotionCam Outdoor works as part of the Ajax security system by connecting to the hub via [Jeweller](#) and [Wings](#) encrypted radio protocols. The communication range without obstacles is up to 1,700 meters.

[Buy MotionCam Outdoor](#)

## Functional elements

1. Hood visor to protect camera and masking sensors from snow and rain
2. Camera
3. LED indicator
4. Motion detector lens
5. Infrared (IR) backlight for taking pictures in the dark
6. SmartBracket mounting plate. To remove the plate, slide it down



The perforated part is necessary to trigger a tamper in case of any attempt to detach the detector from the surface. Do not detach it!

7. The hole for attaching SmartBracket mounting panel with a screw
8. Power button
9. Tamper button. Triggers when an attempt is made to detach the detector from the surface or remove the mount
10. Detector QR code. Is used to connect to the Ajax security system
11. Scrollbar for adjusting the detection range

## Operating principle

MotionCam Outdoor is an outdoor motion detector with a camera. IR sensors of the detector identify intrusions by detecting moving objects with temperatures close to that of the human body. Visual verification helps you instantly assess the situation, relieving users of unnecessary anxiety, and security companies — from false calls of patrols.

[Learn more about Ajax motion detectors](#)

In the armed mode, the detector constantly reads signals from infrared (IR) sensors. When motion is detected, MotionCam Outdoor transmits an alarm to the hub and signals it by flashing the LED indicator (if indication is enabled).

An alarm is detected if both IR sensors detect a movement. The detector takes 1 to 5 photos at a time (depending on the settings) and transmits them to the hub. You can enable the Send Photo in Case of Alarm function in the [detector settings](#).

When triggered, the hub activates sirens, starts scenarios, and notifies users and the security company. In case of an alarm, photos are transmitted to the monitoring station of the security company and to all users of the system who have access to the hub's event feed. All alarms, photos, and events of MotionCam Outdoor are recorded in the event feed of the Ajax app.



The detector doesn't go into the armed mode instantly. The time for switching to armed mode depends on two factors: exit delays (specified in the detector settings) and the hub – detector ping interval (Jeweller settings, the default value is 36 seconds). In the first case, the delay is set by the user. In the second case, the delay is caused by the fact that the hub notifies the detector about the transition to the armed mode not instantly, but within one ping interval.

The range of motion detection is set manually – with a scrollbar on the detector body – and is from 3 to 15 meters. This allows you to accurately set the detection area and avoid false triggerings on bushes, trees, or other objects.

Users know exactly where motion is detected. The notifications contain the name of the hub (name of the guarded object), the name of the device, and the virtual room to which the detector is assigned.

## Photo verification of alarms

00:00

00:08



Wings

The delivery time of a photo to Ajax apps depends on the selected image resolution, Jeweller and Wings signal strength, and the internet speed at the hub. The alarm signal is transmitted in 0.15 seconds.

Photo resolution	Delivery time of one photo
320 × 176 (default)	Up to 9 seconds
640 × 352	Up to 20 seconds

The table shows the delivery time for one photo when the signal strength between the hub and MotionCam Outdoor is 2–3 bars and the hub is connected via Ethernet.

## Temperature compensation

The detector perceives a person and other objects as heat spots. The device monitors these heat spots and, if they move, signals an alarm. MotionCam Outdoor reacts to the movement of heat spots with the temperature close to that of the human body.


In the case where the ambient temperature is about the temperature of the human body, the correct operation of the detector is not guaranteed unless

temperature compensation is applied. Owing to it, the detector identifies movement over the entire operating temperature range.

Temperature compensation is used in all Ajax motion detectors. This way they effectively detect movement over the entire operating temperature range of the detector.

[Learn more](#)

## Pet immunity



00:00

00:14

When set up and installed correctly, MotionCam Outdoor ignores animals up to 80 centimeters tall. The detector has two IR sensors and raises an alarm only when movement is detected by both sensors.

If installed correctly, animals will only enter the detection zone of one of the detector's sensors. This way, MotionCam Outdoor eliminates false alarms. And for additional protection against false alarms, the detector uses the LISA software algorithm.

[Why motion detectors react to animals and how to avoid it](#)

## Anti-masking system

Masking is an attempt to block the view of the detector by painting over it, covering it, placing an obstacle in front of the detector's lens, or otherwise.

MotionCam Outdoor detects the following types of masking:

1. Obstacle in front of the detector's lens at a distance of up to 10 centimeters (the limit distance depends on the type of material).
2. Painting over the detector lens.
3. Sticking over the detector lens.

Masking type	Time to alarm, seconds	Time to restore, seconds
Obstacle in front of the detector's lens (at a distance of up to 10 centimeters from the lens)	7	20
Painting over the detector lens	100	20
Sticking over the lens or detector's side	100	20

The system informs the users and the monitoring station of the security company about masking. For additional protection and notification, enable the reaction of sirens to masking (you can do this in the detector [Settings](#)).

The maximum time of masking detection is 180 seconds (depends on the type of obstacle and the distance to it).



Note that the anti-masking system is always active and works regardless of the detector or system security mode.

For additional protection of the camera or the masking detection system from false alarms on heavy rain or snow, a Hood visor is provided.

### [Anti-masking and its implementation in Ajax outdoor detectors](#)

## Protection against false triggering



00:00

00:14

MotionCam Outdoor features two independent IR sensors, the signals of which are analyzed by a two-stage LISA algorithm. As soon as both IR sensors detect movement, LISA performs correlation and spectral analysis of the signals, which allows you to instantly distinguish between real threats and interference.

### **Correlation analysis**

Each time a motion is detected, the LISA algorithm analyzes and compares the waveforms of two signals in real-time. If the waveforms are similar, the detector triggers an alarm.

### **Spectral analysis**

When both sensors detect motion, but correlation analysis does not reveal sufficient similarity of waveforms, LISA compares the frequency components of the signals from the two sensors.

## **Sending events to the monitoring station**

The Ajax security system can transmit alarms to the central monitoring station (CMS) in such protocol formats as **Sur-Gard (ContactID)**, **SIA DC-09**, and other proprietary protocols. A complete list of supported protocols is [available here](#).

### **Which CMSs can the Ajax security system be connected to**

The device ID and the loop (zone) number can be found in [its states](#). Note that photos are sent to the monitoring station of the security company only if the CMS software supports the transmission of photo verifications. The list of CMSs that support Ajax photo verification is [available here](#).



Photo verifications are available in the [Ajax PRO Desktop CMS](#) without additional setup.

## Adding to the system



The detector is incompatible with Hub and Hub Plus hubs, ReX radio signal range extender, third-party security central units, as well as ocBridge Plus and uartBridge integration modules.

## Before adding a device


1. Install the [Ajax app](#). Create an [account](#). Add a hub to the app and create at least one virtual room.
2. Make sure that the hub is on and has access to the internet (via Ethernet cable, Wi-Fi, and/or mobile network). You can do this in the Ajax app or by checking the hub logo on the faceplate. The logo should light up white or green if the hub is connected to the network.
3. Make sure the hub is disarmed and does not start updates by checking its status in the Ajax app.



Only a user or PRO with administrator rights can add a device to the hub.

[Types of accounts and their rights](#)

## How to add MotionCam Outdoor to the system

1. Open the Ajax app. If your account has access to multiple hubs, select the one to which you want to add MotionCam Outdoor.
2. Go to the **Devices**  tab and click **Add Device**.
3. Name the detector, scan or type in the QR code (placed on the detector body and the packaging), select a room and a group (if [group mode](#) is enabled).
4. Click **Add**; the countdown will begin.



## 5. Switch on the device by holding the power button for 3 seconds.




To make sure MotionCam Outdoor is connected to the hub, the detector must be located at the same secured facility as the system (within the range of the hub's radio network).







The detector connected to the hub will appear in the list of hub devices in the Ajax app. Updating the statuses of devices in the list depends on the Jeweller settings; the default value is 36 seconds.






If the connection fails, try again in 5 seconds. Note that if the maximum number of devices has already been added to the hub (depending on the hub model), you will be notified when you try to add a new one.

MotionCam Outdoor only works with one hub. When connected to a new hub, the detector stops sending commands to the old hub. Once added to a new hub, MotionCam Outdoor is not removed from the device list of the old hub. This must be done through the Ajax app.

## Icons


The icons represent some of MotionCam Outdoor statuses. You can see them in the **Devices**  tab in the Ajax app.


Icon	Value
	Jeweller signal strength – displays the signal strength between the hub and the detector
	MotionCam Outdoor battery level
	Malfunction detected. A list and description are available in the detector states
	The detector operates in <b>Always Active</b> mode <a href="#"><u>Learn more</u></a>
	Entry and/or exit delay is enabled
	<a href="#"><u>Learn more</u></a>

	MotionCam Outdoor will work when <b>Night Mode</b> is enabled  <a href="#">Learn more</a>
	MotionCam Outdoor has detected motion
	MotionCam Outdoor is temporarily disabled  <a href="#">Learn more</a>
	MotionCam Outdoor has been disabled due to the exceeding of the number of alarms  <a href="#">Learn more</a>
	MotionCam Outdoor has temporarily disabled tamper triggering events  <a href="#">Learn more</a>

## States

The states include information about the device and its operating parameters. The states of MotionCam Outdoor can be found in the Ajax app:

1. Go to the **Devices**  tab.
2. Select MotionCam Outdoor from the list.

Parameter	Value
Malfunction	<p>Clicking on  opens the MotionCam Outdoor malfunctions list.</p> <p>The field is displayed if a malfunction is detected</p>
Temperature	<p>Detector temperature, which is measured on the processor and changes gradually.</p> <p>Acceptable error between value in the app and room temperature: 2–4°C</p>
Jeweller Signal Strength	Signal strength between the hub and

	<p>MotionCam Outdoor. Recommended values – 2-3 bars.</p> <p>Jeweller is a protocol for transmitting MotionCam Outdoor events and alarms</p>
<p>Battery Charge</p>	<p>The battery charge level of the device:</p> <ul style="list-style-type: none"> <li>• <b>OK</b></li> <li>• <b>Battery low</b></li> </ul> <p>When the batteries are discharged, the Ajax apps and the security company will receive appropriate notifications.</p> <p>After sending a low battery notification, the detector can work for up to 2 months.</p> <p><b><u><a href="#">How the battery charge is displayed</a></u></b></p> <p><b><u><a href="#">Battery life calculator</a></u></b></p>
<p>Lid</p>	<p>The status of the detector’s tamper that responds to detachment or removal attempts:</p> <ul style="list-style-type: none"> <li>• <b>Opened</b></li> <li>• <b>Closed</b></li> </ul> <p><b><u><a href="#">Learn more</a></u></b></p>
<p>Delay When Entering, s</p>	<p>Delay time when entering (5 to 120 seconds).</p> <p>Delay when entering (alarm activation delay) is the time the user has to disarm the security system after entering the secured area</p> <p><b><u><a href="#">Learn more</a></u></b></p>
<p>Delay When Leaving, s</p>	<p>Delay time when leaving (5 to 120 seconds).</p> <p>Delay when leaving (arming delay) is the time the user has to leave the secured area after arming</p> <p><b><u><a href="#">Learn more</a></u></b></p>



Connection	<p>Connection status between the hub and the MotionCam Outdoor detector:</p> <ul style="list-style-type: none"> <li>• <b>Online</b> – the detector is connected</li> <li>• <b>Offline</b> – no connection to the detector</li> </ul>
Wings Signal Strength	<p>Wings signal strength between the hub and MotionCam Outdoor. Recommended values – 2-3 bars.</p> <p>Wings is a protocol for transmitting MotionCam Outdoor photo verification in case of an alarm</p>
Camera	<p>MotionCam Outdoor camera status:</p> <ul style="list-style-type: none"> <li>• <b>Online</b> – camera is enabled and can take photos</li> <li>• <b>Offline</b> – there is no connection with the detector camera on Wings frequencies</li> </ul>
Sensitivity	<p>Sensitivity level of the motion detector:</p> <ul style="list-style-type: none"> <li>• <b>Low</b></li> <li>• <b>Medium</b></li> <li>• <b>High</b></li> </ul>
Anti-masking	<p>Detector masking state:</p> <ul style="list-style-type: none"> <li>• <b>Alarm</b> – masking detected</li> <li>• <b>On</b> – the anti-masking system is on</li> <li>• <b>Off</b> – the anti-masking system is off</li> </ul> <p><a href="#"><b>Learn more</b></a></p>
Always Active	<p>If active, the detector is always in the armed mode and detects motion</p> <p><a href="#"><b>Learn more</b></a></p>
Temporary Deactivation	<p>Shows the status of the device temporary deactivation function:</p>

	<ul style="list-style-type: none"> <li>• <b>No</b> – the device operates normally and transmits all events</li> <li>• <b>Lid only</b> – the hub administrator has disabled notifications about triggering on the device body</li> <li>• <b>Entirely</b> – the hub administrator has entirely excluded the detector from the system. The device does not execute system commands and does not report alarms or other events</li> <li>• <b>By number of alarms</b> – the device is automatically disabled when the number of alarms is exceeded (specified in the <a href="#">Devices Auto Deactivation</a> settings). The feature is configured in the Ajax PRO app</li> </ul> <p><a href="#">Learn more</a></p>
Firmware	Detector firmware version
ID	Detector ID. Also available on the QR code on the detector body and the packaging
Device №	Number of the device loop (zone)


## Settings

Note that the motion detection range is set using a switch on the detector body.

### To change the detector settings in the Ajax app:

1. Go to the **Devices**  tab.
2. Select MotionCam Outdoor from the list.
3. Go to **Settings** by clicking on the gear icon .
4. Set the parameters.
5. Click **Back** to save the new settings.

Settings	Value
First field	Detector name. Displayed in the list of hub devices, SMS text, and in notifications in the

	<p>event feed.</p> <p>To change the detector name, click on the pencil icon  .</p> <p>The name can contain up to 12 Cyrillic characters or up to 24 Latin characters</p>
Room	<p>Selecting the virtual room to which the MotionCam Outdoor is assigned. The name of the room is displayed in the SMS text and in notifications in the event feed</p>
Sensitivity	<p>Choosing the sensitivity level of the motion detector:</p> <ul style="list-style-type: none"> <li>• <b>Low</b></li> <li>• <b>Normal</b> (default)</li> <li>• <b>High</b></li> </ul> <p>The sensitivity level is selected based on the results of the <a href="#">detection zone test</a>. If during the test the detector doesn't react to motion in 5 cases out of 5, the sensitivity can be increased</p>
Anti-masking	<p>When this option is enabled, MotionCam Outdoor detects masking</p> <p><a href="#">Learn more</a></p>
Always Active	<p>If active, the detector is always in the armed mode and detects motion</p> <p><a href="#">Learn more</a></p>
Alarm LED indication	<p>Allows you to disable the flashing of the detector LED in case of alarm, tamper triggering, or masking detection</p>
Image resolution	<p>Selecting the image resolution (in pixels):</p> <ul style="list-style-type: none"> <li>• 320 × 176</li> <li>• 640 × 352</li> </ul>

	<p>The higher the resolution, the more detailed the image is. However, keep in mind that high resolution will increase the delivery time of photos to the hub</p> <p><a href="#"><u>Learn more</u></a></p>
<p>Send photo in case of alarm</p>	<p>Selecting the number of photos in case of alarm:</p> <ul style="list-style-type: none"> <li>• No photo</li> <li>• 1 photo</li> <li>• Series of 2</li> <li>• Series of 3</li> <li>• Series of 4 (only available at 320 × 176 resolution)</li> <li>• Series of 5 (only available at 320 × 176 resolution)</li> </ul>
<p>Alarms with photo verification</p>	<p>Selecting the number of alarms that are accompanied by photos. You can specify 1 to 10 alarms or set up the transmission of a photo each time the device is triggered.</p> <p>The limit is reset once the security system is disarmed.</p> <p>The setting is available only when the <b>Always Active</b> option is disabled. In this mode, the detector will always transmit photos in case of alarm</p>
<p>Delay When Entering, s</p>	<p>Delay time when entering (5 to 120 seconds).</p> <p>Delay when entering (alarm activation delay) is the time the user has to disarm the security system after entering the secured area</p> <p><a href="#"><u>Learn more</u></a></p>
<p>Delay When Leaving, s</p>	<p>Delay time when leaving (5 to 120 seconds).</p> <p>Delay when leaving (arming delay) is the time the user has to leave the secured area after arming</p>

	<p><a href="#"><u>Learn more</u></a></p>
Delays in Night Mode	<p>If active, the delays when entering and leaving apply to the <b>Night Mode</b>.</p> <p>The field is displayed and active if delays are enabled, as well as the <b>Arm in Night Mode</b> feature</p> <p><a href="#"><u>Learn more</u></a></p>
Arm in Night Mode	<p>If active, the detector switches to the armed mode when <b>Night Mode</b> is enabled</p> <p><a href="#"><u>Learn more</u></a></p>
Alert with a siren if motion is detected	<p>If active, <a href="#"><u>sirens</u></a> added to the system are activated when motion is detected by the MotionCam Outdoor detector</p>
Alert with a siren if masking is detected	<p>If active, <a href="#"><u>sirens</u></a> added to the system are activated when the sensors of the MotionCam Outdoor detector are masked.</p> <p>The field is displayed and active if the <b>Anti-masking</b> option is enabled</p>
Jeweller Signal Strength Test	<p>Switches the detector to the Jeweller signal strength test mode.</p> <p>The test checks the signal strength between the hub and the detector at Jeweller frequencies to determine the optimum installation place</p> <p><a href="#"><u>Learn more</u></a></p>
Detection Zone Test	<p>Switches the detector to the detection zone test mode.</p> <p>The test checks how the detector responds to motion and masking and determines the optimum installation place.</p> <p><b>4 test types are supported:</b></p> <ul style="list-style-type: none"> <li>• Upper sensor of the detector</li> </ul>



	<ul style="list-style-type: none"> <li>• Lower sensor of the detector</li> <li>• Masking sensors</li> <li>• All motion sensors together</li> </ul> <p><a href="#"><u>Learn more</u></a></p>
Wings Signal Strength Test	<p>Switches the detector to the Wings signal strength test mode.</p> <p>The test checks the signal strength between the hub and the detector at Wings frequencies to determine the optimum installation place</p> <p><a href="#"><u>Learn more</u></a></p>
Signal Attenuation Test	<p>Switches the detector to the signal attenuation test mode.</p> <p>The test decreases or increases the radio transmitter power to simulate a change in the environment to check the stability of communication between the detector and the hub</p> <p><a href="#"><u>Learn more</u></a></p>
Temporary Deactivation	<p>Allows the user to disconnect the device without removing it from the system. Two options are available:</p> <ul style="list-style-type: none"> <li>• <b>Entirely</b> – the device will not execute commands or participate in automation scenarios. The system will ignore device alarms and other notifications</li> <li>• <b>Lid only</b> – the system will ignore notifications about the triggering of the device tamper only</li> </ul> <p><a href="#"><u>Learn more</u></a></p> <p>The system can also automatically deactivate devices when the set number of alarms is exceeded</p> <p><a href="#"><u>Learn more</u></a></p>

User Manual	Opens the MotionCam Outdoor User Manual in the Ajax app
Unpair Device	Unpairs the detector, disconnects it from the hub, and deletes its settings

## Photo verification of alarms in Ajax apps

If the **Send photo in case of alarm** option is enabled for MotionCam Outdoor, alarms in Ajax apps will be accompanied by a series of photos (the number depends on the settings). To view the photos, click on the alarm notification in the events feed.

A series of photos are played back in the application as animation, so the user is able to evaluate the unfolding of the incident over time.

To save a series of photos, click on the button highlighted in the screenshot. You can save each frame individually (in JPEG format) or the entire series (in GIF or MP4 format).

[Learn more about photo verification](#)

## Indication

The MotionCam Outdoor LED indicator may light up red or green, depending on the status of the detector.

### Indication when pressing the power button

Indication	Event
Lights up red while the button is pressed	Pressing the power button when the detector is on
Lights up green while the device is being activated	Turning on
First lights up red, then flashes three times and goes off	Turning off

### Active detector indication

Indication	Event
Lights up green for 1 second	Alarm, masking, or tamper triggering
Flashes red after the first power on	Hardware error. The detector needs to be repaired, please contact <a href="#">Support Service</a>
Flashes red a few minutes after being installed in the mount	Calibration failed – something was obstructing the detector’s view during calibration, or it was not installed correctly.  Recalibrate the detector. To do this, remove the device from the mount and reinstall it. Recalibration will start automatically. Make sure that nothing obstructs the view of the detector
Lights up green for a few seconds	Connecting the detector to the hub
In case of alarm, masking, or tamper triggering, slowly lights up and goes out in green	Detector batteries need to be replaced. Battery replacement instructions are available <a href="#">here</a>


## Functionality testing

The Ajax security system has several tests for choosing the right installation place for the devices. MotionCam Outdoor tests do not start straight away but not later than over a single hub-detector ping period (36 seconds under default settings of the hub). You can change the ping period of devices in the **Jeweller** menu of the hub settings.

**There are 4 tests available for MotionCam Outdoor:**

- [Jeweller Signal Strength Test](#)
- [Wings Signal Strength Test](#)
- [Detection Zone Test](#)
- [Signal Attenuation Test](#)

**To run a test, in an Ajax app:**

1. Select the hub if you have several of them or if you are using a PRO app.
2. Go to the **Devices**  menu.
3. Select MotionCam Outdoor.

## Detector placement



MotionCam Outdoor is suitable for the protection of the area around the secured site. It may guard a courtyard of a private house, a parking, unheated premises, and other sites. The detector can be installed both outdoors and indoors.

**The detector is placed 0.8 – 1.3 meters above ground level.** This height is a prerequisite for the effective work of the pet immunity function. Placement at a different height can lead to false alarms due to pets or to poor detection of human movement.

The detector should be installed on a flat stable surface, for example on the wall of a house or on a fence. If the detector is installed on an unstable surface, this may lead to false alarms.

The top beam of the detector should be aimed parallel to the ground. If the area is not flat, the installation height is calculated from the highest point of the monitored area.

When choosing a location, consider 2 main factors: **signal strength** and **detection zone**.

# Signal strength

Locate MotionCam Outdoor in a place with stable Jeweller and Wings signal strength (2-3 bars in the Ajax app). When choosing a place for installation, consider the distance between the detector and the hub and the presence of any obstacles between the devices hindering the radio signal passage: walls, intermediate floors, or large-size objects located in the room.



Be sure to check the Jeweller and Wings signal strength at the installation site. If the signal strength is low (a single bar), we cannot guarantee stable operation of the security system! At the very least, relocate the device as repositioning even by 20 cm can significantly improve the signal reception.

Note that MotionCam Outdoor does not work with ReX radio signal range extenders, so connect it directly to the hub.

## Detection zone

The detection distance is adjusted using the **Detection Distance** scrollbar on the rear panel of the detector. When choosing the installation location, consider the maximum detection range of the detector. It depends on the sensitivity, the position of the Detection Distance scrollbar, the type and speed of the person's movement (running, walking), and the ambient temperature.



The detection distance was tested at the medium sensitivity level, the ambient temperature of +23°C, and clear weather. Motion type – walking. Other conditions may produce different results.


When choosing where to place the detector, be sure to use the Detection Zone Test to determine the sector in which the detector recognizes motion as accurately as possible.

Make sure that no obstacles block the view of the detector. Note that MotionCam Outdoor does not detect movement behind the glass. Therefore, do not install the detector in locations where an open window or door can obstruct its view.

When installing, also consider the width of the detection zone. Incorrect detector placement can lead to false alarms.

00:00

00:07



Avoid the situations where the detector identifies movement at a greater distance than required. To do this, adjust and set the desired detection distance. This will reduce the likelihood of false alarms in response to external factors.

Do not install the detector in a place where bushes or trees may come within the detection zone of the two IR sensors of the detector. In summer or in warm weather, this can lead to false alarms of the detector.


## Do not install the detector

- Near the metal objects and mirrors. They can shield and attenuate the radio signal.
- Opposite the trees with leaves in the detection zone of both IR sensors of the detector. This can lead to false alarms in warm weather.
- In places where the detection zone of the detector might include bushes 80 centimeters high or above. This can lead to false alarms in warm weather.
- In places with low or unstable signal strength.
- Closer than 1 meter to the hub.

## Detector installation



Before installing MotionCam Outdoor, be sure to select the optimal location following the requirements of this manual! Before installation, be sure to set up the desired detection distance of the detector (Detection Distance scrollbar).



### To install MotionCam Outdoor:

1. Temporarily attach the SmartBracket panel with the bundled ties (or other temporary fasteners, such as double-sided adhesive tape). Installation height is 0.8 – 1.3 meters from the ground.



The detector should be installed at the recommended height to ensure the correct operation of the pet immunity function. To install the SmartBracket mount on ties, first make holes in it.

2. Install the detector on the SmartBracket panel.
3. Leave the detector detection zone (horizontal angle of view – 90°) and make sure there is no movement within the detector field of view. This is necessary for correct calibration of the masking sensors. During the calibration, the detector will flash green around once per second. Calibration takes up to 2 minutes.



The masking sensors calibration starts automatically as soon as the detector body is attached to SmartBracket.



4. Perform **Signal Strength** and **Attenuation** tests. If the signal strength is unstable or one bar is displayed, move the detector or hub.
5. Run **detection zone tests**, first for the lower sensors and then for the upper ones. This will help determine and set the required maximum detection distance of the detector (determined by the lower sensor). Then, run the detection zone test for both sensors simultaneously, as well as the masking sensors test. If there is no response to movement, select the appropriate sensitivity level, detection distance (Detection Distance scrollbar), and check the tilt angle of the detector.
6. Attach the SmartBracket mounting panel to the surface using the bundled screws. When attaching, use at least two fixing points. To make the tamper react to attempts to detach the device, be sure to fix the perforated corner of SmartBracket.



Ties or double-sided adhesive tape should be used for temporary attachment only. The device attached by adhesive tape may come unstuck from the surface and fall at any time. In addition, the device may fail if hit. Note that while the device is secured with ties or adhesive tape, the tamper will not trigger if the detector is detached from the surface.

7. Attach MotionCam Outdoor to the mounting plate, wait for the calibration to complete, and tighten the screw at the bottom of the body. The screw is needed for more reliable fastening and protection of the detector from quick dismantling.
8. Once the detector is attached firmly to SmartBracket, the LED will flash to indicate that the tamper has been triggered. If the LED does not light up after the device is attached to SmartBracket, check the tamper status in the Ajax app and then make sure the panel is firmly attached.



The Hood visor is used to protect the camera and to avoid false alarms of the masking detection system in heavy rain or snow.

## Maintenance

Check the functioning of the detector on a regular basis. The optimal frequency of checks is once every three months. Clean the detector body from dust, cobwebs, and other contaminants as they emerge. Use a soft dry cloth suitable for equipment care.

Do not use substances that contain alcohol, acetone, gasoline or other active solvents to clean the detector. Wipe the lens gently as scratches may impair the detector sensitivity.

The pre-installed batteries provide up to 3 years of battery life at the rate of 1 alarm per day with the standard Jeweller settings (ping period – 36 seconds). If the detector batteries are nearly depleted, the security system will send an appropriate notification, and the LED will light up and go out gradually when the detector detects any movement or if the tamper triggers.

MotionCam Outdoor can work up to 2 months after the low battery signal. However, we recommend that you replace the batteries immediately upon notification. It is advisable to use lithium batteries. They have a large capacity and are less affected by temperatures.

### How long Ajax devices operate on batteries, and what affects this

How to replace batteries in MotionCam Outdoor detector

## Technical Specifications

Classification	Radio-interlinked photoelectric security detector
Installation method	Outdoors and indoors
Type of detector	Wireless
Jeweller radio protocol	Transmission of events and alarms Alarm delivery time: 0.15 s
Wings radio protocol	Transmission of a series of photos Photo delivery time under default settings: up to 9 seconds
Compatibility	Hub 2, Hub 2 Plus

	Doesn't work with ReX range extenders
Sensing element	Two IR sensors
Sensitivity	Adjustable, 3 levels
Motion detection distance	From 3 to 15 meters (set by user)
Horizontal viewing angle of the detector	90°
Motion detection speed	From 0.3 to 2.0 m/s
Pet immunity option	<p>Yes. When installed and set up correctly, the detector ignores animals up to 80 centimeters tall</p> <p><a href="#"><u>Learn more</u></a></p>
Camera angle	<ul style="list-style-type: none"> <li>• Horizontal – 105°</li> <li>• Vertical – 102°</li> </ul>
Distortion	Barrel, -77%
Sending photo in case of alarm	<p>Photo resolution:</p> <ul style="list-style-type: none"> <li>• 320 × 176 pixels (default)</li> <li>• 640 × 352 pixels</li> </ul> <p>Shooting series of up to 5 photos</p> <p><a href="#"><u>Learn more</u></a></p>
Infrared backlight for shooting in the dark	Yes
Protection against false triggering	+
Tamper protection	+
Protection against masking	+
Temperature sensor	+
CMS compatibility	<p>Motion alarms are transmitted to CMSs that support SIA (DC-09) and Contact ID protocols</p> <p><a href="#"><u>CMS software with support for photo-verification of alarms</u></a></p>

Frequency band	868.0–868.6 MHz or 868.7–869.2 MHz, depending on the sales region
Maximum radio signal strength	20 mW limit
Radio signal modulation	GFSK
TDMA	+
Radio signal range	Up to 1,700 m (without obstacles)
Ping interval	From 12 to 300 seconds
Power supply	4 CR123 batteries
Power supply voltage	6 V
Battery life	Up to 3 years (up to 2.5 years with <b>Entry Delay</b> setting enabled)  <a href="#">Calculate the battery life</a>
Protection class	IP55
Operating temperature range	From –25°C to +60°C
Operating humidity	Up to 95%
Dimensions	206 × 108 × 93 mm
Weight	470 g
Service life	10 years
Warranty	24 months  <a href="#">Learn more</a>

### Compliance with standards

## Complete set

1. MotionCam Outdoor
2. SmartBracket mounting plate
3. Hood visor
4. Four CR123 batteries (pre-installed)

5. Installation kit

6. Quick Start Guide

## Warranty

The warranty for the AJAX SYSTEMS MANUFACTURING Limited Liability Company products is valid for 2 years after purchase and does not apply to the bundled batteries.

If the device does not function correctly, please contact the Support Service first. In half of the cases, technical issues can be solved remotely!

[Warranty Obligations](#)

[User Agreement](#)

Technical support: [support@ajax.systems](mailto:support@ajax.systems)