




# Data sheet thermostats X3D



<b>WIRELESS PROGRAMMABLE THERMOSTAT, Part No°: TAP X3D 310EL</b>	<b>WIRELESS RECEIVERS, Part No°: REC X3D 122</b>	<b>WIRELESS RECEIVERS, Part No°: REC X3D 311</b>
		
<ul style="list-style-type: none"> <li>• 10 year autonomy with lithium batteries</li> <li>• Bidirectional wireless</li> <li>• Eco-friendly indicator</li> <li>• Electric consumption (kWh) of the associated electrical heating devices</li> <li>• Optional smartphone &amp; tablet control</li> <li>• Digital clock thermostat with a low pro file design for time-dependent monitoring and control of room temperature</li> <li>• Temperature set quickly via rotary switch</li> <li>• Info key for viewing important settings</li> <li>• Quick start-up via 3 basic programs with individually changeable comfort and reduced temperature</li> <li>• Party program</li> <li>• Fully automatic summer/winter-time correction</li> <li>• Holiday program with reduction phase or date-controlled heating phase for holiday homes</li> <li>• 24 programmable time phases per program also enable reduction phases during the day</li> <li>• Plug-in base for wall or flush-mounted socket installation</li> <li>• Default protocol: X3D, bidirectional</li> <li>• Radio frequency: 868 MHz</li> <li>• Operating voltage: Two 1,5V LR03 / AAA lithium batteries</li> <li>• Plug-in base for wall or flush-mounted socket installation</li> <li>• Dimensions: 135x81x22 mm (HxBxP)</li> </ul>	<ul style="list-style-type: none"> <li>• Bidirectional receiver (X3D)</li> <li>• Compatible with most of the X3D transceivers (Tydom 1.0, touch screens, remote app..)</li> <li>• Strip terminal</li> <li>• Easy to install</li> <li>• Possibility to switch to X2D protocol (monodirectional)</li> <li>• Regulation: PI or On/Off</li> <li>• Default protocol: X2D</li> <li>• Radio frequency: 868 MHz</li> <li>• Mounting: Wall-mounted (using clips and screw)</li> <li>• Switching capacity: 230 V, 16 A 3500W max</li> <li>• Dimensions: 114x54x25mm (HxBxP)</li> </ul>	<ul style="list-style-type: none"> <li>• Bidirectional plug receiver (X3D)</li> <li>• Compatible with most of the X3D transceivers (Tydom 1.0, touch screens, remote app..)</li> <li>• Easy to install</li> <li>• Possibility to switch to X2D protocol (monodirectional)</li> <li>• Radio frequency: 868 MHz</li> <li>• Switching capacity: 230V~ 16A 3500W max</li> <li>• Dimensions: 150x75x40mm (HxBxP)</li> </ul>